User Manual

Version 1.0 April 2015



Copyright 2015 All Rights Reserved Manual Version 1.0

> The information contained in this document is subject to change without notice. We make no warranty of any kind with regard to this material, including, but not limited to, the implied warranties of merchantability and fitness for a particular purpose. We shall not be liable for errors contained herein or for incidental or consequential damages in connection with the furnishing, performance, or use of this material.

> This document contains proprietary information that is protected by copyright. All rights are reserved. No part of this document may be photocopied, reproduced or translated to another language without the prior written consent of the manufacturer.

TRADEMARK

Intel®, Pentium® and MMX are registered trademarks of Intel® Corporation. Microsoft® and Windows® are registered trademarks of Microsoft Corporation. Other trademarks mentioned herein are the property of their respective owners.

Safety IMPORTANT SAFETY INSTRUCTIONS

- 1. To disconnect the machine from the electrical Power Supply, turn off the power switch and remove the power cord plug from the wall socket. The wall socket must be easily accessible and in close proximity to the machine.
- 2. Read these instructions carefully. Save these instructions for future reference.
- 3. Follow all warnings and instructions marked on the product.
- 4. Do not use this product near water.
- 5. Do not place this product on an unstable cart, stand, or table. The product may fall, causing serious damage to the product.
- 6. Slots and openings in the cabinet and the back or bottom are provided for ventilation; to ensure reliable operation of the product and to protect it from overheating. These openings must not be blocked or covered. The openings should never be blocked by placing the product on a bed, sofa, rug, or other similar surface. This product should never be placed near or over a radiator or heat register, or in a built-in installation unless proper ventilation is provided.
- 7. This product should be operated from the type of power indicated on the marking label. If you are not sure of the type of power available, consult your dealer or local power company.
- 8. Do not allow anything to rest on the power cord. Do not locate this product where persons will walk on the cord.
- 9. Never push objects of any kind into this product through cabinet slots as they may touch dangerous voltage points or short out parts that could result in a fire or electric shock. Never spill liquid of any kind on the product.

CE CE MARK This device with regard Directive"

This device complies with the requirements of the EEC directive 2004/108/EC with regard to "Electromagnetic compatibility" and 2006/95/EC "Low Voltage Directive"

FC

FCC

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference.

(2) This device must accept any interference received, including interference that may cause undesired operation

CAUTION ON LITHIUM BATTERIES

There is a danger of explosion if the battery is replaced incorrectly. Replace only with the same or equivalent type recommended by the manufacturer. Discard used batteries according to the manufacturer's instructions.



Battery Caution

Risk of explosion if battery is replaced by an incorrectly type. Dispose of used battery according to the local disposal instructions.



Safety Caution

Note: To comply with IEC60950-1 Clause 2.5 (limited power sources, L.P.S) related legislation, peripherals shall be 4.7.3.2 "Materials for fire enclosure" compliant.

4.7.3.2 Materials for fire enclosures

For MOVABLE EQUIPMENT having a total mass not exceeding 18kg.the material of a FIRE ENCLOSURE, in the thinnest significant wall thickness used, shall be of V-1 CLASS MATERIAL or shall pass the test of Clause A.2.

For MOVABLE EQUIPMENT having a total mass exceeding 18kg and for all STATIONARY EQUIPMENT, the material of a FIRE ENCLOSURE, in the thinnest significant wall thickness used, shall be of 5VB CLASS MATERIAL or shall pass the test of Clause A.1

LEGISLATION AND WEEE SYMBOL

2012/19/EU Waste Electrical and Electronic Equipment Directive on the treatment, collection, recycling and disposal of electric and electronic devices and their components.



The crossed dustbin symbol on the device means that it should not be disposed of with other household wastes at the end of its working life. Instead, the device should be taken to the waste collection centers for activation of the treatment, collection, recycling and disposal procedure.

To prevent possible harm to the environment or human health from uncontrolled waste disposal, please separate this from other types of wastes and recycle it responsibly to promote the sustainable reuse of material resources.

Household users should contact either the retailer where they purchased this product, or their local government office, for details of where and how they can take this item for environmentally safe recycling.

Business users should contact their supplier and check the terms and conditions of the purchase contract.

This product should not be mixed with other commercial wastes for disposal.

Revision History

Revision	Date	Description
V1.0	April, 2015	Release

Table of Contents

1 Item C	hecklist	1
1-1	Standard Items	1
1-2	Optional Items	2
2 Syster	n View	3
2-1	Front View & Rear View	
2-2	Side View	4
2-3	Bottom View	4
2-4	Dimension & View Angle	5
2-5	I/O View	7
3 Syster	n Assembly & Disassembly	8
3-1	Install the Power Adapter	8
3-2	Replace the HDD	9
3-3	Replace the SSD Card	9
4 Periph	erals Installation	10
4-1	Install the MSR Module	
4-2	Install the iButton Module	
4-3	Install the Addimat Key Reader	
4-4	Install the Customer Display (Graphic LCM)	
4-5	Install the 2 nd Display	14
	4-5-1 How to activate the 2 nd display Under Windows	
4-6	Install the Wall Mount Kit	
4-7	Install the Cash Drawer	21
5 Specif	ication	23
6 Config	uration	25
6-1	D36 Motherboard Layout	25
6-2	Connectors & Functions	26
6-3	Jumper Settings	27
Appendi	x: Driver Installation	30

1 Item Checklist

1-1 Standard Items



1-2 Optional Items



2-1 Front View & Rear View



Number	Description
1	LED indicator
2	Touch screen
3	Thumb screw for the cable cover
4	Ventilation hole
5	HDD door
6	VFD/2 nd display dummy cover
7	MSR/iButton/Addimat key module dummy cover
8	Swing arm base

2-2 Side View



Fold down the swing arm base



2-3 Bottom View



Number	Description
1	Rubber foot
2	Power adapter (with holder bracket)
3	IO ports

2-4 Dimension & View Angle









2-5 I/0 View



Number	Description
а	Line out
b	Display port
С	Mic in
d	Power button
е	19V DC in
f	VGA
g	COM1~3 (from right to left)
h	USB x 4 (USB2.0)
i	Cash drawer
j	USB x 2 (USB3.0)
k	LAN

3 System Assembly & Disassembly

3-1 Install the Power Adapter

The system is equipped with a 65W power adapter. Please follow the steps below to install the power adapter.

- The swing arm base is designed to allow for clean cable management. There is a cable channel through the swing arm base, which has a quick access cover. Please loosen the thumb screw (x1) of the cable cover first.
- 2. Lay down system to access the bottom of the base. Remove the screws (x2) of the holder bracket.
- 3. Attach the power adapter and then replace the holder bracket.





- 4. Route the cable as shown in the picture.
- 5. Connect the power adapter to the 19V DC IN port.
- 6. Replace the cable cover.

3-2 Replace the HDD

1. Remove the HDD/SSD cover retaining a screw and sliding the drive out.

2. Unclip the HDD cover from the drive as shown in the picture.

- **3-3 Replace the SSD Card**
 - 1. Remove the HDD/SSD cover retaining a screw and sliding the drive out.

2. Remove the screws (x4) that fix the SSD card to the bracket.

9









4 Peripherals Installation

4-1 Install the MSR Module

MSR is installed on the right side of the system. Please make sure the unit is powered down before starting.

1. Remove the dummy cover first.



- 2. Connect the MSR cable (x1) to the connector on the system side.
- 3. Insert the MSR module in place and fasten the screws (x2) on the back to secure the module.





4-2 Install the iButton Module

iButton is installed on the left side of the system. Please make sure the unit is powered down before starting.

1. Remove the dummy cover first and then unfasten the screws (x2).

- 2. Connect the iButton cable to the connector on the system side.
- 3. Insert the iButton module in place and fasten the screws (x2) on the back to secure the module.



4-3 Install the Addimat Key Reader

Addimat key reader is an option instead of iButton module. It is also installed on the left side of the system. Please make sure the unit is powered down before starting.

1. Remove the dummy cover first and then unfasten the screws (x2).

- 2. Connect the addimat key reader cable to the connector on the system side.
- 3. Insert the addimat key reader in place and fasten the screws (x2) on the back to secure the module.



4-4 Install the Customer Display (Graphic LCM)

1. Remove the dummy cover first.

- After the dummy cover is removed, plug the 8-pin LCM cable into the CN8 / LCM connector on the system board.
- 3. Fasten the screws (x2) to secure the LCM display to the system.





The Customer Display is directly connected to COM6 and uses the following communication parameters: 9600, N, 8, 1.

4-5 Install the 2nd Display

1. Remove the dummy cover first.

- After the dummy cover is removed, plug the 20-pin 2nd display cable into the CN6 connector on the system board.
- 3. Fasten the screws (x2) to secure the 2^{nd} display to the system.



4-5-1 How to activate the 2nd display Under Windows

- Make sure to connect the 2nd display cable and begin the installation after your system has booted.
- The Setup program requires about one minute for the installation. If you turn the power off or remove the 2nd display cable while the Setup program is running, it may cause an error with the Windows operating system.
- The optimal resolution for this USB monitor is 1024 x 600.
- When the installation is completed, configure the following settings to activate the 2nd display.



2. Click the **Control Panel** to change the setting and customize the functionality of the system.



4. Select **Display** from the menu and the display properties windows appears.

Flytech	11	J2 RFID Configurat	Control Panel P	
Computer	J2 RFID Tool	111	Change the appearance of your displays Detect Image: Im	
Revork	RW-Everyt.		Display: 1. Mobile PC Display Resolution: 1366 × 768 (recommended) Orientation: Landscape Unitiple display: Show desktop only on 1 Duplicate these displays This is currently so: Extend these displays This is currently on Extend these displ	
Panel			OK Cancel Apply	Windows Embedded Buid 701 This copy of Windows is not genuine
@	Ø			EN 🥦 📢 🕪 🔀 🎼 6:12 PM 3/5/2010

5. Arrange the monitors displayed in the order they are actually used.

Flytech	11	J2 RFID	Comparison Compariso	Search Control Ponel
	, I	Configurat	Change the appearance of your displays	
Computer	J2 RFID Tool			Detect [
Network	sleeper		Display: 1. Mobile PC Display	
			Resolution: 1366 × 768 (recommended) v Orientation: Landscape v	
Recycle Bin	RW-Everyt		Multiple displays: Extend these displays	
Control Panel	test		This is currently your main display. Make text and other items larger or smaller What display settings should I choose?	Advanced settings
			ОК Салс	el Apply
				Windows Embedded Build 7601 This copy of Windows is not genuine
6. I	Reme	mbe	r to click Apply before exiting the menu.	L× t⊕ v t⊕ to to 3/5/2010
New D		2 2 8 - 100	en ar ed Freendalante + Digly + Scare feedalante - e [1] Scare Conse Feed	
		0	hange the appearance of your displays	
			Dayla Series Do you want to keep these display settings?	
C III	-		noklan metekan Maré dagia	
			Ter med lands Appl John enlang Alabasia (Jangar, Kan Careff yang menan fuglagi Alabasia (Jante Jangar) And Appl yattings decall (Januar)	
			C Gert App	Darry 1
-	-	673	Westing Tolested Discourse of Manager of Manager of Manager 20 ar - 2 - 2 - 2 - 2 - 2 - 2 - 2 - 2 - 2 -	

7. Click Keep Changes and then click OK to save the setting.

4-6 Install the Wall Mount Kit

The wall mount come with the following parts:



1. First attach the four mounting clips using the 3 mm screws as shown in the picture.

2. Next attach the mounting bracket to the wall or other surface using at least four of the bracket mounting holes. Please note that the bracket has both a 100mm and 75mm hole pattern, so that the bracket can be used with the VESA bracket as well as being directly mounted to a wall.





- Next step is to route any cables you need to go to the system as required. A space is provided just by the power supply for the cable to exit cleanly, assuming they are routed via the swing arm cable channel as in a normal install.
 Cables can also be routed down as well. Be sure cables are clear or protected of any sharp surfaces. You can remove the system on and off the wall mount bracket as needed to route the cables.
- Cables can exit the top or bottom when routed between the bracket and system. A wall hole could be used to cover the cables in the power supply area.
- 5. The final step is to install the locking safety screw. This screw is to insure the system is not knocked of the wall by accident . The 4 mm screw supplied is used for this propose. First remove the rubber hole plug from the system, then screw in the safety screw. The system is now secure enough and the swing base can be adjusted to the desired viewing angle.





Some possible viewing angles using the wall mount bracket.





4-7 Install the Cash Drawer

You can install a cash drawer through the cash drawer port. Please verify the pin assignment before installation.

Cash Drawer Pin Assignment



Pin	Signal
1	GND
2	Cash drawer 1 Out
3	Cash drawer 1 In
4	12V / 19V (OR 24v)
5	Cash drawer 2 Out
6	GND

Cash Drawer Controller Register

The Cash Drawer Controller use one I/O addresses to control the Cash Drawer.

Register Location:0x482hAttribute:Read / Write

Size: 8bit

BIT	BIT7	BIT6	BIT5	BIT4	BIT3	BIT2	BIT1	BIT0
Attribute	CD2 Out	Reserved	CD2 In	CD1 Out	CD1 In		Reserved	t



- Bit 7: Cash Drawer 2 pin output control
- Bit 6: Reserved

Bit 5: Cash Drawer 2 pin input control

- Bit 4: Cash Drawer 1 pin output control.
- = 1: Opening the Cash Drawer
- = 0: Allow close the Cash Drawer
- Bit 3: Cash Drawer 1 pin input control.
- = 1: the Cash Drawer closed or no Cash Drawer
- = 0: the Cash Drawer opened
- Bit 2: Reserved
- Bit 1: Reserved
- Bit 0: Reserved

Note: Please follow the Cash Drawer control signal design to control the Cash Drawer.

Cash Drawer Control Command Example

Use Debug.EXE program under DOS or Windows98

Con	nmand	Cash Drawer
0 482 04		Opening
0 482 00		Allow to close
Set the I/O address		482h bit4 =1 for opening Cash Drawer by "DOUT bit0"
pin control.		
Set the I/O address		482h bit4 = 0 for allow close Cash Drawer.

Com	nmand	Cash Drawer
148	2	Check status
\triangleright	The I/O address 482	2h bit3 =1 mean the Cash Drawer is opened or not exist.
\triangleright	The I/O address 482	h bit3 =0 mean the Cash Drawer is closed.

Specification

Model Name	J2 240		
Motherboard	D36		
CPU support	Intel Bay Trail SoC Celeron J1900 2.0GHz, L2 2MB, TDP 10W (default)		
Chipset	NA		
System memory	DDR3L S.O. DIMM x1, FSB 1066/1333hz, default 2G, max. 8G		
Graphic memory	Intel HD Graphic DX11.1		
LAN controller	Realtek RTL8111E-VL-CG 10/100/1000 baseT LAN		
Audio controller	Realtek ALC662VD0-GR		
I/O controller	Winbond NCT6106D		
Touch controller	to be defined major SKU with PCAP only or both PCAP/TF RES.Touch		
BIOS	Phoenix UEFI code		
Board dimension	185 (W) x 130 (D) mm		
LCD Touch Panel			
LCD size	14" LED panel		
Brightness	200 nits up		
Maximal resolution	1366*768		
Touch screen type	True Flat resistive touch (USB) True Flat projected capacitive touch (USB)		
Tilt angle	0°~90°		
Storage			
HDD	one 2.5" SATA HDD bay, 320 GB standard		
SSD	8/16/32/64 GB option (built-in 2.5" HDD cover)		
Expansion			
mini PCI-E socket	1 for 802.11 b/g/n and broadband wireless		
Front I/O			
Power LED	1 Green Powered up, Amber in Standby (3-pin power LED connector)		
Side I/O			
USB (2.0)	1		
External Rear I/0			
USB 2.0	4		
USB 3.0/2.0	1		
Serial/COM	3 x RJ45 COM ports(COM1/COM2 powered COM with power enable/disable by BIOS setting; default COM1 is 5V; COM2 is 12V; COM3 is 12V)		
LAN(10/100/1000)	1		
DC jack	1		

Model Name	J2 240				
Motherboard	D36				
Cash drawer	1 x RJ 11 (12V/24V cash drawer), jumper setting, default 24V				
Display port	1				
Power button	1				
Audio jack	1 x Line-out / 1x Mic-in				
Speaker					
speaker	1 x 2W				
Power					
Power adapter	Ext. 65W/19V				
Peripherals	·				
MSR module	MSR 3 track (USB, secured head)				
2-in-1 Reader	MSR (USB) + RFID (125KHz USB)				
Customer display	2x20 LCM (TTL for 225/NINÔ, COM for 680), Winstar WH2002L-TFH-ET#				
2 nd display	10.1" (16:9) LED panel, 1024x600 or above, 200~220 nits (all electronics on system BD, cable only to display), DP mode				
iButton Addimat key reader	Connector read head, 2 wire connection to board, controller shared w/ MSR				
Barcode scanner	1D /2D scanner module				
UPS battery	4S/1P , 4S/2P battery kit (Internal, PSU external)				
Communication					
Wireless LAN	Optional, mini-PCIE				
Certifications	·				
EMC and Safety	FCC Class A, CE, LVD				
Environment					
Operating temperature	5°C ~ 40 °C (41 °F ~ 104 °F)				
Storage temperature	-20 °C ~ 70 °C (-4 °F ~ 158 °F)				
Humidity	20% ~ 80% RH non condensing				
Dimension (W x D x H)	Head: 346x210x37.5mm Base: 186x170x26mm System Max. height 268mm				
Weight (N.W./G.W.)	3.7kg / 4.7kg				
Mounting	75mm x75mm VESA standard holes				
OS support	Windows 7 ,POSReady 7 Windows® Embedded 8.1 Industrial Pro retail Windows® Embedded 8.1 Industry Pro Linux				
* This specification is subject to change without prior notice.					

6 Configuration



6-1 D36 Motherboard Layout

6-2 Connectors & Functions

Connector	Function		
CN1	Front I/O board		
CN2	Inverter connector		
CN3	LVDS connector		
CN6	System FAN connector		
CN7	LPT port connector		
CN8	Speaker & MIC connector		
CN9	40pin external connector		
CN10	HDD LED connector		
CN11	Power LED connector		
CN12	SATA power connector		
CN13/14	USB port (internal)		
CN15	PS2 keyboard connector		
CN16	LPT touch		
CN17	MSR connector		
CN18	COM5 (touch) connector		
CN19	Wide Range		
CN20	Power button (internal)		
CN21	LCM connector		
CN22	POS325 51pin connector		
PWR1/PWR2	DC Jack		
RJ11_1	Cash drawer connector		
RJ45_1	LAN connector		
RJ45_2	COM1/ COM2		
RJ48_1	COM3		
DDR3_A1	DDR3 SO-DIMM		
SATAO/SATA2	SATA		
USB1/USB2	USB2.0		
USB3	USB3.0		
VGA1	CRT connector		
SW1	Power button		
MINI_PCIE1	MINI PCIE		
JP1	Inverter select		
JP4	LCD ID setting		
JP6	Cash drawer power setting		
JP7	Touch connector		

6-3 Jumper Settings

Inverter Selection

Function	JP1 (1-2) (3-4)
▲ LED	1 3 2 4
CCFL	1 3 2 4

Cash Drawer Power Setting

Function	JP6 (1-2) (3-4)
▲+19V	1 3 2 4
+12V	1 3 2 4

LCD ID Setting

Panel	anel Becolution		VDS	Output	JP4
Number	Resolution	Bits	Channel	Interface	(1-2) (3-4) (5-6) (7-8) (9-10)
1	800 x 600	18	Single	LVDS Panel	1 3 5 7 9 2 4 6 8 10
2	800 x 600	24	Single	LVDS Panel	$ \begin{array}{c} 1 \\ 2 \\ 4 \\ 6 \\ 8 \\ 10 \end{array} $
3	1024 x 768	18	Single	LVDS Panel	1 3 5 7 9 2 4 6 8 10
4	1024 x 768	24	Single	LVDS Panel	$ \begin{array}{cccccccccccccccccccccccccccccccccccc$
5	1366 x 768	18	Single	LVDS Panel	1 3 5 7 9 2 4 6 8 10
6	1366 x 768	24	Single	LVDS Panel	$ \begin{array}{cccccccccccccccccccccccccccccccccccc$

7	1024 x 600	18	Single	LVDS Panel	$ \begin{array}{cccccccccccccccccccccccccccccccccccc$
8	1280 x 1024	24	Dual	LVDS Panel	1 3 5 7 9 2 4 6 8 10
9	1440 x 900	24	Dual	LVDS Panel	1 3 5 7 9 2 4 6 8 10
15	1920 x 1080	24	Dual	LVDS Panel	1 3 5 7 9 2 4 6 8 10
				CRT	1 3 5 7 9 2 4 6 8 10

COM1/COM2/COM3 Power Setting

COM1, COM2 and COM3 can be set to provide power to your serial device. The voltage can be set to +5V or +12V in the BIOS.

	Phoenix SecureCore Technology Setup	
Main Advanced <u>Security</u>	Boot Exit	
Setup Warning: Setting items on this screen to in values may cause system to malfund > CPU Configuration > South Configuration > Intel(R) Smart Connect Technology	correct stion!	Item Specific Help VGA/COM Power Configuration
OS Selection • SIO Configuration • HW Monitor • Power Configuration • VGA/COM Power Configuration	[Windows7]	tun Dofaulto
Esc Exit	↔ Select Menu Enter Select > Sub-Menu F10 S	ave and Exit

- 1. Power on the system, and press the key when the system is booting up to enter the BIOS Setup utility.
- 2. Select the Advanced tab.
- 3. Select VGA/COM Power Configuration Ports and press <Enter> to go to display the available options.



4. To enable the power, select COM1, COM2 or COM3 Power setting and press <Enter>. Select Power and press <Enter>. Save the change by pressing F10.

Appendix: Driver Installation

To download the most recent drivers and utilities, and obtain advice regarding the installation of your equipment, please visit the J2 Technical Support Website:

http://www.j2retailsystems.com/support.php